Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

IN THE CLAIMS:

1.   (Previously amended) A radio-frequency amplifier comprising:

a transistor having an input terminal, an output terminal, a control terminal, and a transconductance g_m;

a series-connected feed-through impedance connected in parallel with the input terminal and the output terminal of the transistor;

a load resistance R_L connected to the output terminal of the transistor; and

wherein the control terminal of the transistor is biased at a fixed voltage, and the transistor and a signal source impedance r_s satisfy the equation:

$$g_m = \frac{1}{r_s}\left(\frac{\delta\alpha}{\gamma}(1+\chi)^2\eta(\omega_o)+\eta^2(\omega_o)\right)^{-\frac{1}{2}}$$

where

δ	$=$	a gate noise coefficient of the transistor,
α	$=$	a ratio of g_m to a channel conductance at zero drain-to-source voltage of the transistor, g_{d0},
γ	$=$	a channel thermal noise coefficient of the transistor,
χ	$=$	a ratio of a backgate transconductance g_{mb} of the transistor to g_m.
ω_o	$=$	an operation frequency, and
$\eta(\omega_o)$	$=$	a ratio of a gate admittance g_g of the transistor to g_m.

2.   (Original) The radio-frequency amplifier of claim 1 further comprising a tank circuit connected between a voltage source V_{dd} and the input terminal of the transistor.

3.   (Previously amended) The radio-frequency amplifier of claim 1 wherein the transconductance g_m of the transistor is larger than $1/r_s$.

-2-

           10/731,832

4.   (Previously amended) The radio-frequency amplifier of claim 1 wherein the feed-through impedance is formed by a real resistor R_P in parallel with the transistor drain-source small-signal resistance r_{ds}.

5.   (Previously amended) The radio-frequency amplifier of claim 3 wherein the feed-through impedance further comprises an inductance L_P.

Claim 6 (cancelled).

7.   (Previously amended) The radio-frequency amplifier of claim 2 wherein the tank circuit comprises a parallel combination of a resistance, a capacitance, and an inductance.

Claims 8-11 (cancelled).

12.   (Currently amended) A radio-frequency ~~amplifer~~ **amplifier** comprising:

a common gate amplifier having an input and an output; and

a feed-through circuit having a resistance R_f coupled in parallel with the common gate amplifier, wherein the resistive feed-through circuit reduces output noise power, and the common gate amplifier and a signal source impedance r_s satisfy the equation:

$$g_m = \frac{1}{r_s}\left(\frac{\delta\alpha}{\lambda}(1+\chi)^2\eta(\omega_o)+\eta^2(\omega_o)\right)^{-\frac{1}{2}}$$

where

g_m =   an amplifier transconductance,

δ =   a gate noise coefficient of the amplifier,

α =   a ratio of g_m to a channel conductance at zero drain-to-source voltage of the amplifier, g_{d0},

γ =   a channel thermal noise coefficient of the amplifier,

χ =   a ratio of a backgate transconductance g_{mb} of the amplifier to g_m,

ω_o =   an operation frequency, and

$\eta(\omega_o)$ =   a ratio of a gate admittance g_g of the amplifier to g_m.

13.   (Previously amended) The radio-frequency amplifier of claim 12 wherein the feed-through circuit further comprises an inductance L_p.

-3-

D1245806v1-13641.0060 DOC

14.   (Previously amended) The radio-frequency amplifier of claim 12 wherein the feed-through circuit comprises a feed-through resistance R_P and a feed-through capacitance C_P.

Claim 15 (cancelled).

16.   (Currently amended) A radio-frequency ~~amplifer~~ **amplifier** comprising:

a common gate amplifier having an input and an output; and

common gate amplifier transconductance and feed-through means for reducing transistor noise that is passed on to the load**, wherein the common gate amplifier transconductance and feed-through means satisfies the equation**:

$$g_m = \frac{1}{r_s}\left(\frac{\delta\alpha}{\lambda}(1+\chi)^2 \eta(\omega_o) + \eta^2(\omega_o)\right)^{-\frac{1}{2}}$$

where

g_m	=	**an amplifier transconductance,**
r_s	=	**signal source impedance**
δ	=	**a gate noise coefficient of the amplifier,**
α	=	**a ratio of g_m to a channel conductance at zero drain-to-source voltage**

of the amplifier, g_{d0},

γ	=	**a channel thermal noise coefficient of the amplifier,**
χ	=	**a ratio of a backgate transconductance g_{mb} of the amplifier to g_m,**
ω_o	=	**an operation frequency, and**
$\eta(\omega_o)$	=	**a ratio of a gate admittance g_g of the amplifier to g_m.**

Claim 17 (cancelled).

18.   (Previously presented) The radio-frequency amplifier of claim 16 comprising:

a first stage including the common gate amplifier transconductance and feed-through means;

a second stage coupled to the first stage including a common-source amplifier with inductive degeneration; and

-4-

D1245806v1-13641.0060 DOC

PAGE 5/10 * RCVD AT 1/19/2006 6:22:04 PM [Eastern Standard Time] * SVR:USPTO-EFXRF-6/30 * DNIS:2738300 * CSID: * DURATION (mm-ss):02-48

a third stage coupled to the second stage including a common-source amplifier with inductive degeneration.

19.   (Previously presented) The radio-frequency amplifier of claim 16 wherein the common gate amplifier transconductance and feed-through means further comprises a resistance R_f.

20.   (Previously presented) The radio-frequency amplifier of claim 19 wherein the resistance R_f is formed by a resistance R_P in parallel with a transistor drain-source resistance r_{ds}.

21. , (Previously presented) The radio-frequency amplifier of claim 16 wherein the common gate amplifier transconductance and feed-through means further comprises an inductance L_p.

22.   (Previously presented) The radio-frequency amplifier of claim 16 driven by a signal source with output impedance r_s, wherein a transconductance g_m of the radio-frequency amplifier is larger than $1/r_s$, a series-connected resistor R_f and capacitor C_f is connected between the input terminal and the output terminal of the radio-frequency amplifier, so that the real part of an input impedance of the radio-frequency amplifier is increased.

23.   (Previously presented) The radio-frequency amplifier of claim 1 wherein oscillation is prevented by ensuring that the real part of an input port impedance Z_{in} and the real part of an output port impedance Z_{out} are positive, where $Re[Z_{in}]$ and $Re[Z_{out}]$ can be expressed as

$$Re[Z_{in}] = \frac{R_f + Re[Z_L]}{1 + g_m R_f (1 + \chi)}$$
$$Re[Z_{out}] = R_f + [g_m R_f (1 + \chi) + 1]Re[Z_S]$$

where

R_f = a feed-through resistance,

Z_S = a source impedance, and

Z_L = a load impedance.

-5-

D1245806v1-13641.0060 DOC

24.   (Previously presented) The radio-frequency amplifier of claim 12 wherein oscillation is prevented by ensuring that the real part of an input port impedance Z_{in} and the real part of an output port impedance Z_{out} are positive, where $Re[Z_{in}]$ and $Re[Z_{out}]$ can be expressed as

$$Re[Z_{in}] = \frac{R_f + Re[Z_L]}{1 + g_m R_f (1 + \chi)}$$
$$Re[Z_{out}] = R_f + [g_m R_f (1 + \chi) + 1]Re[Z_S]$$

where

R_f =   a feed-through resistance,

Z_S =   a source impedance, and

Z_L =   a load impedance.

25.   (Previously presented) The radio-frequency amplifier of claim 16 wherein oscillation is prevented by ensuring that the real part of an input port impedance Z_{in} and the real part of an output port impedance Z_{out} are positive, where $Re[Z_{in}]$ and $Re[Z_{out}]$ can be expressed as

$$Re[Z_{in}] = \frac{R_f + Re[Z_L]}{1 + g_m R_f (1 + \chi)}$$
$$Re[Z_{out}] = R_f + [g_m R_f (1 + \chi) + 1]Re[Z_S]$$

where

g_m =   an amplifier transconductance,

R_f =   a feed-through resistance,

Z_S =   a source impedance,

Z_L =   a load impedance, and

χ =   a ratio of a backgate transconductance g_{mb} of the amplifier to g_m.

26.   (New) A radio-frequency amplifier comprising:

a common gate amplifier having an input and an output; and

common gate amplifier transconductance and feed-through means for reducing transistor noise that is passed on to the load, wherein the common gate amplifier transconductance and feed-through means further comprises a resistance R_f, and the resistance R_f is formed by a resistance R_P in parallel with a transistor drain-source resistance r_{ds}.

-6-

D1245806v1-13641.0060 DOC

27.   (New) The radio-frequency amplifier of claim 26 further comprising common gate amplifier transconductance and feed-through means for reducing transistor noise that is passed on to the load, wherein the common gate amplifier transconductance and feed-through means further comprises an inductance L_p.

28.   (New) A radio-frequency amplifier comprising:

a common gate amplifier having an input and an output; and

common gate amplifier transconductance and feed-through means for reducing transistor noise that is passed on to the load, driven by a signal source with output impedance r_s, wherein a transconductance g_m of the radio-frequency amplifier is larger than $1/r_s$, a series-connected resistor R_f and capacitor C_f is connected between the input terminal and the output terminal of the radio-frequency amplifier, so that the real part of an input impedance of the radio-frequency amplifier is increased.

29.   (New) A radio-frequency amplifier comprising:

a common gate amplifier having an input and an output; and

common gate amplifier transconductance and feed-through means for reducing transistor noise that is passed on to the load, 16 wherein oscillation is prevented by ensuring that the real part of an input port impedance Z_{in} and the real part of an output port impedance Z_{out} are positive, where $Re[Z_{in}]$ and $Re[Z_{out}]$ can be expressed as

$$Re[Z_{in}] = \frac{R_f + Re[Z_L]}{1 + g_m R_f (1 + \chi)}$$
$$Re[Z_{out}] = R_f + [g_m R_f (1 + \chi) + 1] Re[Z_S]$$

where

g_m	=	an amplifier transconductance,
R_f	=	a feed-through resistance,
Z_S	=	a source impedance,
Z_L	=	a load impedance, and
χ	=	a ratio of a backgate transconductance g_{mb} of the amplifier to g_m.